


?????

LI-COR HOBOLink



4-20??, ???? , ??? , ???? , ???? (Ah), ?? , ???? , ?? , ?? , ????kWh? , ???? , ??? , ???? , ???? (PF), ???? , ??? , ???? , ???? , ???? , ?? , ???? , ???? (Wh), ?? (W), ?

- ????????
- ???????IP66/NEMA 4X??
- ???????
 - ??1.7 W????????????
 - ??MicroRX Station?RX2102??MicroRX????RX2104??HOBOnet??MicroRX Station?RX2106????5 W?15 W????????
 - ??????AA??
- ????????????
- ?????HOBOnet????????RX2106?
- MicroRX????????RX2103??MicroRX????????RX2104????????????
- ??LCD???????????
- ???????????????U?????
- ????????????????
- ??4G????????????10????
- ??LI-COR Cloud????????????

- HOBO RX2100 MicroRX ?
- ?????
- ??
- ?????
- ??AA????RX2101?RX2103??????
- ???RX2102?RX2104??????

- Contact Product Support www.onsetcomp.com/support/contact
- Call 1-508-759-9500
- In U.S. toll free 1-877-564-4377

????? (RX2100) Specifications

????	??RX????????? RX2101 ? RX2105???RX????????????? RX2103????????? -40°C ? 60°C?-40°F ? 140°F? ??RX????????????? RX2102???RX????????????????? RX2104????? HOBOnet ??RX????????????? RX2106????????? -20°C ? 60°C?-4°F ? 140°F?
????????	5
????????????	??100??328???
??????????	?? 15 ?????????????????????????????????
??????	1??-18??
?????	? 0°? 40°C?32°F? 104°F????????????±8 ?? ? -40°? 60°C?-40°F? 140°F????????????±30 ??
????? ??	RX2102?RX2104 ? RX2106???? 1.7 ?????????????????????P-AC-1?????????SOLAR-xW????????????? RX2101?RX2103 ? RX2105?6 ? 1.5 ?????????????P-AC-1?
??????	RX2102?RX2104?RX2106????? ?-20°C?40°C?-4°F?104°F????????????3-5????????????????? ????????????????? • ???±40°????????10???? • ???????10????????30???? ???5W?15W????????? • ?????????10???? • ????????????????????? ????????????????? 1??????? • RX2102?3?? • RX2104?2?? • RX2106?3?? RX2101?RX2103????? ????????? • RX2101?1?????????1? • RX2103?2?????????1? ?????1????????? • RX2101?3?? • RX2103?2?? ????????????????? RX2105????? ????????????????????????????1????????????????????3????1????????????????????2????10?????????????????????????????
??	16MB?100?????????
??????	?????2-4?????
????	????????????????????????????
?????	?????? 0° ? 50°C?32° ? 122°F????????????????????????????????
??	????????? ???????????????????????? ?????????????????????????™??????U?????????????????
??	19.95 × 13.68 × 7.49 ?? (7.85 x 5.39 x 2.95 ??)
??	678? (23.9??)
??	??? U ??????????? 4.14 ???1.63 ?????????????????????
????	?????NEMA 4X ? IP66 (??????????)
????	GSM/GPRS/EDGE: Quad band 850/900/1800/1900 MHz UMTS/HSPA+: Seven band 800/850/900/1800/1900/2100 MHz LTE: Twelve Band 700/800/850/900/1800/1900/2100/2600 MHz
??	4G LTE
??	

???????? - RX2105 ? RX2106 ?? RX ????? FCC ??? QIPPLS62-W?IC ?????7830A-PLS62W

